

3G Model name	Ericsson F3607gw	Ericsson F5521gw	Sierra MC8790V	Sierra Compass 888	BandLux C270
Form Factor					
Form Factor	mini PCI-E (USB 2.0 signal)	mini PCI-E (USB 2.0 signal)	mini PCI-E (USB 2.0 signal)	USB Port (USB 2.0 signal)	USB Port (USB 2.0 signal)
Platform					
JetBox 9560 / 9460	●	●	●	●	●
JetBox 9500 / 9400 / 5400				●	●
JetBox 3300 / 3350 (from firmware V1.8)				●	●
JetBox 8180	●	●	●	●	●
JetBox 8150 / 8152				●	●
Modes					
HSPA	●	●	●	●	●
WCDMA	●	●	●	●	●
EDGE	●	●	●	●	●
GPRS	●	●	●	●	●
Bands					
UMTS/ WCDMA/ HSPA	2100/1900/850 or 2100/1900/900 MHz	2100/1900/900/850MHz (Band I / II /V/VI /VIII)	850/1900/2100 MHz	850/1900/2100 MHz	2100 MHz
GSM	850/900/1800/1900MHz	1900/1800/900/850MHz	850/900/1800/1900 MHz	850/900/1800/1900 MHz	850/900/1800/1900 MHz
Referenced Speeds*					
HSPA	●	●	●	●	●
D/L	7.2Mbps	7.2Mbps	7.2 Mbps	7.2 Mbps	7.2 Mbps
U/L	2.0Mbps	5.76 Mbps	5.76 Mbps	5.76 Mbps	5.76 Mbps
EDGE/GPRS	●	●	●	●	●
D/L	247.4Kbps	247Kbps	--	--	--
U/L	123.7Kbps	247Kbps	--	--	--
GPS					
Standalone	●	●			
A-GPS	●	●			

*Reference from each module's data sheet and HSPA regulations